Amphenol®



RADLOK™

Utilizing Amphenol's latest R4 RADSOK® Technology, our RADLOK $^{\text{TM}}$ product line was designed to be compact and

Power Interconnect products in today's market often require additional mounting hardware (e.g. washers, clamps, bolts, nuts, etc.) making them prone to costly labor expenses for installation and routine maintenance.

Features:

- Voltage Rating: 1000V
 Current Rating: 70A 400A
 Tool-Free Mechanical Locking
 High cycle durability (500 mating cycles)
 RoHS complaint
 Available in Black, Red, Orange (custom colors available upon request)

www.amphenol-industrial.com



Dimensions

RADLOK™ Connector (Tubular Version)												
RADLOK™ Size (mm)	W	N	Н	h	D	P						
3.6	15.5	38.0	18.3	7.3	8.1	27.0						
5.7	18.5	47.7	22.9	9.4	11.2	33.0						
8.0	21.6	56.0	27.7	11.8	14.6	38.8						
10.0	26.0	61.0	35.3	15.9	17.5	37.0						
10.3	26.0	61.0	35.3	15.9	17.5	37.0						
12.0	28.5	70.5	35.9	15.0	20.0	44.5						

RADLOK™ Connector (Stamped Version)

RADLOK™ Size (mm)	w	N	Н	h	D	P	
5.7	18.5	46.0	21.9	9.2	11.2	30.0	
8.0	21.7	54.4	27.7	12.5	14.6	34.3	
10.0	25.7	65.0	33.3	16.1	17.5	35.7	



70

300

400

120

300

400

120

200

70

120

200

350

120 33.9 7.8 Ф 7.0

40.2 12.8 Ф 10.0

47.4 12.8 Ф 12.0

47.4 12.8 Ф 12.0

47.9 15.8 Φ 14.5

32.5 13.1 Ф 13.7 19.2 42.1 16.2 Ф 16.2 21.7

62 23.0 Φ 20.2 25.7 65 25.5 Φ 22.2 27.7

42.8 13.1 **D** 13.7 19.2

51.2 16.2 Ф 16.2 21.7

78.5 23.0 Ф 20.2 25.7

80.2 25.5 Ф 22.2 27.7

5.7

10

12

5.7

10

10.3

12

5.7

10

10.3

12

3.6

5.7

10.3

Pi

Feed Thru

Thread

Lug

Pin

16.1	17.5	35.7
	AVI	
100		
	4	

CDEGLMNPQSW

N/A N/A 26.4 32.2

48.4 19.6 Φ 18.2 23.7 N/A 21 30 10 62 23.0 Φ 20.2 25.7 N/A 24 33 16 M4

42.9 13.1 Φ 19.6 11.6 6 16 24.5 16.5 M3 51.1 16.2 Φ 21.6 13.6 8 18 27 18.5

62.4 19.6 Φ 23.6 15.6 10.5 21 30 22 71.2 23.0 Φ 25.6 17.6 12.5 24 33 24 M4

71.2 23.0 Φ 25.6 17.6 12.5 24 33 24 76 25.5 Φ 27.6 19.6 14.5 26 36 26

64 19.6 Φ 18.2 23.7 N/A 21 30 N/A 78.5 23.0 Φ 20.2 25.7

21.1

32.2

32.9

10

N/A 10 N/A

10

16 24.5 5 M3 18 27 10

24 33 16 26 36 16

16 24.5

18 27

24 33

1.5

3.2

2.8


6.3

8.5 10.5


10.5

13

M4 4.2 N/A



Tubular Lug Version



Thread

M 6 x 1.0-6g

M 8 x 1.25-6g

M 10 x 1.5-6g

M 10 x 1.5-6g


M 12 x 1.75-6g

M 3 x 0.5-6g M 6 x 1.0-6g

M 8 x 1.25-6g M 10 x 1.5-6g


M 10 x 1.5-6g


M 12 x 1.75-6g























Section A-A





How to Order

Proc Ty		Te	rmination Type	RADSOK®	(mm)	Lug Type	Cable Size (mm²) **	Current (A)	Length (mm)	Cor	ın. Color	Stud Size	F	Pin End	P	lating Type	Modification
		1 2	RDLK + RDLK RDLK + POW LUG	036 057	3.6 5.7		10	70 90/120	E			N/A M/E + STUD SIZE					
MBLY	EMBLY	3	RDLK + POW LUG 45°	080	8.0		35/50	=RATORACIA)				M/E + STUD SIZE					
	CABLE ASSEMBLY	4	RDLK + LUG TRMNL RDLK + RING	100	10.0	N/A	50/70/95	200/250/300	L+ LENGTH	*	ORANGE	M/E + STUD SIZE M/E + STUD SIZE		0237470		1112	/50W0"
CONNECTOR CA	5	6	TRMNL RDLK + BLUNT CUT	103	10.3		95	350				N/A		N/A	N/A	N/A	
		7	RDLK + STRIPPED	120	12.0		120	400				STRIPPED LENGTH (mm)					
	ECTOR	o	RDLK CONNECTOR			1 TUBULAR											
	CONN					2 STAMPED			14/74								
	N N	9	RDLK PIN					1	I/A				10 20 30	THREAD LUG PIN-PIN	2 3	Silver Tin Nickel	*/F1 */F1 */F1

NOTE:

- 1) For all applications, care must be taken to ensure that RADLOK™ connection is protected from the transmittal of any mechanical loads induced by, but not limited to, vibration, bending, the mass of the cable, or shock loading. The cable/wiring should be secured as close to the RADLOK™ as possible. Custom mounting options and recommendations are available upon request.

 2) "Stud Size", M for Metric unit & E for Imperial unit. For example, M8 means Stud Size is 8mm; E3/4 means the Stud Size is ¾ inch.

- Examples:

 10.0mm Orange RADLOK™ connector to 3/8" stud hole Lug Terminal, 10ft long 70mm² cable assembly would have part number, RL4-100-70L3048E3/8

 8.0mm Black RADLOK™ connector with Tubular 50mm² cable crimp would have part number, RL0-080-1-50BK

 8.liver plated 12.0mm RADLOK™ Feed Thru Pin would have part number, RL9-120-101F1

 ** (Leave blank for default connector color or default pin without modification)

 ** (10mm² cable is recommeded for 3.6mm RADSOK®; 16mm²/25mm² cable is recommended for 5.7mm RADSOK®, ...etc)

Europe: Amphenol Industrial Operations Europe Via Barbaiana 5 1-20020 Lainate (MI) Italy Tel: +39 02 93254.204 Fax: +39 02 93254.444

Middle East: Amphenol Middle East Enterprises FZE Office C-37 PO Box 21107 Ajman Free Zone, UAE Tel: +9716-7422494 Fax: +9716-7422941